

GV-COM V2



The GV-COM V2 adds one RS-485 port to your computer through a USB connector. The GV-COM V2 can convert the standard RS-232 signal, through USB connector, to RS-485 2-wire control for PTZ cameras, GV-Data Capture Box or any other RS-485 devices.

Specifications		
OS Supported	32-bit	Windows XP / Windows Vista / Windows 7 / Windows Server 2008
	64-bit	Windows 7 / Windows Server 2008
Serial Interface	RS-485	Signal: RS485+, RS485- Connector: Terminal Resistance Switch (120Ω)
	16 KV ESD for All Signals	Serial Line Protection
USB	Compliance	USB 2.0 Backward Compatible
	Speed	Full speed 12 Mbps
Communication Parameters	Parity	None, Even, Odd
	Data Bit	7, 8
	Stop Bit	1, 2
	Flow Control	RTS / CTS, XON / XOFF
	Speed	600 bps to 115,200 bps
Environmental Conditions	Operation Temperature	0~55°C / 32~131°F
	Humidity	5%~95% (Non-Condensing)
Dimensions(W x H x D)		68.5 x 33.5 x 16 (mm) / 2.7 x 1.32 x 0.63 (in)
Installation Guide		GV-COM V2

Note:

1. All specifications are subject to change without notice.
2. When GV-COM V2 works with [GV-Wiegand Capture](#), GV-COM V2 does not support 64-bit Windows versions currently.